

TREK 40/15

High voltage power amplifier with an all-solid-state design for high slew rate, wide bandwidth, and low-noise operation.

The Trek® 40/15 is a DC-stable, high voltage power amplifier featuring an all solid-state design for high slew rate, wide bandwidth, and low-noise operation. Configured as non-inverting with a fixed gain of 4000 V/V, it is protected against over-voltage and over-current conditions that may be generated by active loads or by output short circuits to ground. The four-quadrant, active output stage sinks or sources current to reactive or resistive loads throughout the output voltage range to achieve the accurate output response and high slew rates demanded by reactive loads.

PRODUCT HIGHLIGHTS

- Four-quadrant output for driving capacitive loads
- Closed loop system for high accuracy
- Short-circuit protected for equipment protection
- All solid-state design for maintenance free operation
- DC-stable for programmable supply applications
- Low output noise for ultra-accurate outputs
- NIST-traceable Certificate of Calibration provided with each unit

TYPICAL APPLICATIONS

- | | |
|--|--|
| <ul style="list-style-type: none"> ■ Dielectric studies ■ Electron beam ion traps and ion sourcing ■ Electrospinning ■ Electrostatic deflection (including ion beam steering) ■ Electrostatic flame control | <ul style="list-style-type: none"> ■ Electrostatic levitation ■ Electrostatic precipitation ■ High-voltage cable testing ■ High-voltage component testing ■ Plasma studies (including dielectric barrier discharge) |
|--|--|



AT A GLANCE

Output Voltage Range

0 to ±40 kVDC or peak AC

Output Current Range

0 to ±15 mA DC or peak AC

Slew Rate

Greater than 350 V/μs

Large Signal Bandwidth (2%)

DC to greater than 1.4 kHz

DC Voltage Gain

4000 V/V Fixed

TREK 40/15 HIGH VOLTAGE POWER AMPLIFIER

TECHNICAL DATA

Performance Specifications		
Output Voltage Range	0 to ± 40 kVDC or peak AC	
Output Current Range	0 to ± 15 mA DC or peak AC	
Input Voltage Range	0 to ± 10 VDC or peak AC	
Input Impedance	25 k Ω , nominal (inverting/differential option: 50 kW, nominal)	
DC Voltage Gain	4000 V/V	
DC Voltage Gain Accuracy	Better than 0.1% of full scale	
DC Offset Voltage	Less than ± 4 V	
Output Noise	Less than 5 V rms ¹	
Slew Rate	Greater than 350 V/ μ s (10% to 90%, typical)	
Small Signal Bandwidth	DC to greater 20 kHz (-3dB)	
Large Signal Bandwidth	DC to greater than 1.4 kHz, typical (2% distortion)	
Stability	Drift with Time: Less than 50 ppm/hr, noncumulative	Drift with Temp: Less than 100 ppm/ $^{\circ}$ C
Voltage Monitor Specifications		
Ratio	1 V / 4000 V	
DC Accuracy	Better than 0.1% of full scale	
DC Offset Voltage	Less than ± 2 mV	
Output Noise	Less than 20 mV rms ¹	
Output Impedance	47 Ω	
Current Monitor Specifications		
Ratio	0.5 V/mA	
DC Accuracy	Better than 2% of full scale	
Offset Voltage	Less than ± 10 mV	
Output Noise	Less than 30 mV rms ¹	
Bandwidth	DC to greater than 5 kHz (-3dB)	
Output Impedance	47 Ω	
Mechanical Specifications		
Dimensions (H x W x D)	1239 x 578 x 893 mm (49 x 22.8 x 35 in)	
Weight	100 kg (220 lb) approximate	
HV Connector	Caton High Voltage Connector	
BNC Connectors	Amplifier Input, Voltage Monitor, Current Monitor, Remote High Voltage ON/OFF, Out of Regulation Status, Fault/Trip Status	
Electrical Specifications		
Line Voltage	180 to 250 VAC at 48 to 63 Hz	
AC Line Receptacle	Standard 3-prong with integral fuse holder	
Power Consumption	1800 VA, maximum	

¹ Measured using the true rms feature of the HP Model 34401A digital multimeter

TECHNICAL DATA**Environmental Specifications**

Temperature	0 to 40°C (32 to 104°F)
Relative Humidity	To 75%, noncondensing
Altitude	To 1524 meters (5000 ft)

Features

High Voltage On/Off	Local: Individual push-button switches	Remote: TTL compatible input. TTL high (or open) turns off high voltage output. TTL low turns on high voltage output.
Dynamic Adjustment	Graduated one-turn panel potentiometer is used to optimize the AC response for various load parameters.	
Current Limit/Trip	Switch selectable for limit or trip. Graduated one- turn panel potentiometer is used to adjust limit or trip level from 0 to ± 15 mA.	
Out of Regulation Status Indicator and Connector	Illuminates and TTL low is provided when unit fails to produce required HV output such as during current limit.	
Limit/Trip Status Indicator and Connector	An indicator will illuminate and a BNC will provide a TTL low when the high-voltage output is disabled due to the output current exceeding the current trip level, the detection of a highvoltage supply fault, the removal of one of the panels, or if the Trek 40/15 is out of regulation for greater than 500 ms.	

REFERENCE NUMBERS**Included Accessories**

PN	Description
23392	Operator's Manual
B3060	Shorting BNC Cap
43466	HV Output Cable
Varies	Line Cord, Spare Fuses (selected per geographic destination)

ABOUT ADVANCED ENERGY

Advanced Energy (AE) has devoted more than three decades to perfecting power for its global customers. AE designs and manufactures highly engineered, precision power conversion, measurement and control solutions for mission-critical applications and processes.

Our products enable customer innovation in complex applications for a wide range of industries including semiconductor equipment, industrial, manufacturing, telecommunications, data center computing, and medical. With deep applications know-how and responsive service and support across the globe, we build collaborative partnerships to meet rapid technological developments, propel growth for our customers, and innovate the future of power.

PRECISION | POWER | PERFORMANCE

For international contact information,
visit advancedenergy.com.

sales.support@aei.com
+1.970.221.0108

Specifications are subject to change without notice. Not responsible for errors or omissions. ©2022 Advanced Energy Industries, Inc. All rights reserved. Advanced Energy®, Trek®, and AE® are U.S. trademarks of Advanced Energy Industries, Inc.